



Izbor motorno zaštitnog prekidača (DM sklopke)

Snaga i struja motora		Podešavanje opsega za zaštitu od preopterećenja	Snaga i struja motora		Podešavanje opsega za zaštitu od preopterećenja
1 -fazni 230 - 240 V			3 -fazni 400 - 415 V		
[kW]	[A]	[A]	[kW]	[A]	[A]
0.06	0.7	0.63 – 1	0.06	0.2	0.16 – 0.25
0.09	0.7	0.63 – 1	0.09	0.3	0.25 – 0.4
0.12	1.3	1 – 1.6	0.12	0.4	0.4 – 0.63
0.18	1.9	1.6 – 2.5	0.18	0.6	0.4 – 0.63
0.25	2.4	1.6 – 2.5	0.25	0.8	0.63 – 1
0.37	2.9	2.5 – 4	0.37	1.1	1 – 1.6
0.55	4.2	4 – 6.3	0.55	1.5	1 – 1.6
0.75	5.6	4 – 6.3	0.75	1.9	1.6 – 2.5
1.1	7.4	6.3 – 10	1.1	2.6	2.5 - 4
1.5	8.9	6.3 – 10	1.5	3.6	2.5 – 4
2.2	14.5	10 – 16	2.2	5.0	4 – 6.3
3	17.8	16 – 20	2.5-3.0	6.6	6.3 – 10
			4.0	8.5	6.3 – 10
			5.5	11.3	10 – 16
			7.5	13.2	10 – 16
			11.0	21.7	16 – 20
			15.0	29.3	25 – 40
			18.5	36.0	25 – 40